

# COMPUTER SCIENCE & INFORMATION TECHNOLOGY

## Discrete and Engg. Mathematics



Comprehensive Theory  
*with Solved Examples and Practice Questions*





**MADE EASY Publications Pvt. Ltd.**

**Corporate Office:** 44-A/4, Kalu Sarai (Near Hauz Khas Metro Station), New Delhi-110016 | **Ph. :** 9021300500

**Email :** infomep@madeeasy.in | **Web :** www.madeeasypublications.org

## Discrete & Engg. Mathematics

© Copyright by MADE EASY Publications Pvt. Ltd.  
All rights are reserved. No part of this publication may be reproduced, stored in or introduced into a retrieval system, or transmitted in any form or by any means (electronic, mechanical, photo-copying, recording or otherwise), without the prior written permission of the above mentioned publisher of this book.



**MADE EASY Publications Pvt. Ltd.** has taken due care in collecting the data and providing the solutions, before publishing this book. In spite of this, if any inaccuracy or printing error occurs then **MADE EASY Publications Pvt. Ltd.** owes no responsibility. We will be grateful if you could point out any such error. Your suggestions will be appreciated.

## EDITIONS

First Edition : 2015  
Second Edition : 2016  
Third Edition : 2017  
Fourth Edition : 2018  
Fifth Edition : 2019  
Sixth Edition : 2020  
Seventh Edition : 2021  
Eighth Edition : 2022  
Ninth Edition : 2023  
Tenth Edition : 2024  
Eleventh Edition : 2025

**Twelfth Edition : 2026**

# CONTENTS

## Discrete & Engg. Mathematics

### CHAPTER 1

#### Propositional Logic ..... 3-20

1.1	Propositional Logic; First Order Logic .....	3
1.2	Logical Connectives or Operators .....	3
1.3	Well-Formed Formulas (WFFs).....	8
1.4	Normal forms of Well-Formed Formulas.....	10
1.5	Rules of Inferences for Propositional Calculus.....	12
1.6	Predicate Calculus .....	13
1.7	Universal and Existential Quantifiers.....	14
	<i>Student Assignments</i> .....	17

### CHAPTER 2

#### Combinatorics.....21-43

2.1	Introduction .....	21
2.2	Permutations.....	22
2.3	Combinations .....	25
2.4	Binomial Identities .....	27
2.5	Generating Functions .....	29
2.6	Summation .....	30
2.7	Recurrence Relations.....	33
2.8	Solving Recurrence Relations.....	34
	<i>Student Assignments</i> .....	39

### CHAPTER 3

#### Set Theory and Algebra ..... 44-92

3.1	Introduction .....	44
3.2	Sets .....	44
3.3	Relations .....	49
3.4	Functions.....	59
3.5	Equal Functions.....	65
3.6	Groups .....	65

3.7	Lattice .....	73
3.8	Types of Lattices.....	78
3.9	Boolean Algebra .....	80
	<i>Student Assignments</i> .....	82

### CHAPTER 4

#### Graph Theory ..... 93-125

4.1	Fundamental Concepts .....	93
4.2	Special Graphs .....	97
4.3	Graph Representations.....	99
4.4	Isomorphism .....	100
4.5	Invariants of Isomorphic Graphs .....	101
4.6	Operations on Graphs.....	102
4.7	Walks, Paths and Cycles .....	103
4.8	Connected Graphs, Disconnected Graphs and Components.....	104
4.9	Euler Graphs .....	108
4.10	Hamiltonian Graphs.....	108
4.11	Planar Graphs.....	109
4.12	Trees .....	110
4.13	Enumeration of Graphs .....	115
	<i>Student Assignments</i> .....	122

### CHAPTER 5

#### Probability..... 126-147

5.1	Some Fundamental Concepts.....	126
5.2	Mean .....	130
5.3	Median.....	131
5.4	Mode and Standard Deviation .....	133
5.5	Standard Deviation.....	133
5.6	Random Variables.....	135
5.7	Distributions.....	135
	<i>Student Assignments</i> .....	141

**CHAPTER 6**

<b>Linear Algebra</b> .....	<b>148-174</b>
6.1 Introduction .....	148
6.2 Special Types of Matrices.....	148
6.3 Algebra of Matrices.....	149
6.4 Properties of Matrices.....	151
6.5 Determinants .....	153
6.6 Inverse of Matrix .....	156
6.7 System of Linear Equations.....	157
6.8 Solution of System of Linear Equation by LU Decomposition Method (Factorisation or Triangularisation Method).....	159
6.9 Eigenvalues and Eigenvectors .....	162
<i>Student Assignments</i> .....	168

**CHAPTER 7**

<b>Calculus</b> .....	<b>175-205</b>
7.1 Limit.....	175
7.2 Continuity.....	179
7.3 Differentiability .....	180
7.4 Mean Value Theorems.....	181
7.5 Theorems of Integral Calculus .....	184
7.6 Methods of Integration .....	184
7.7 Definite Integrals .....	187
7.8 Partial Derivatives.....	191
7.9 Total Derivatives.....	193
7.10 Maxima and Minima (of function of a single independent variable) .....	194
<i>Student Assignments</i> .....	201

# Discrete & Engineering Mathematics

---

## Goal of the Subject

The mathematics of modern computer science is built almost entirely on discrete math, in particular Combinatorics and graph theory. Discrete math will help you with the “Algorithms, Complexity and Computability Theory” part of the focus more than programming language. The understanding of set theory, probability, matrices and combinations will allow us to analyze algorithms. We will be able to successfully identify parameters and limitations of your algorithms and have the ability to realize how complex a problem/solution is.

# Discrete & Engineering Mathematics

---

## INTRODUCTION

---

In this book we tried to keep the syllabus of Discrete & Engineering Mathematics around the GATE syllabus. Each topic required for GATE is crisply covered with illustrative examples and each chapter is provided with Student Assignment at the end of each chapter so that the students get a thorough revision of the topics that he/she had studied. This subject is carefully divided into eight chapters as described below.

### Discrete Mathematics:

1. **Propositional Logic:** In this chapter we study logical connectives, well-Formed formulas, rules for inference, predicate calculus with Universal and Existential quantifiers.
2. **Combinatorics:** In this chapter we discuss the basic principles of counting, permutations, combinations, generating functions, binomial coefficients, summations and finally we discuss the recurrence relations.
3. **Set Theory and Algebra:** In this chapter we discuss the basic terms and definitions of set theory, Operations on sets, relations and types of relations, functions and their types and finally group theory, posets, lattices and boolean algebra.
4. **Graph Theory:** In this chapter we discuss the Special Graphs, isomorphism, vertex and edge connectivity, Euler graphs, Hamiltonian and planar graph, trees and enumeration of graphs.

### Engineering Mathematics:

5. **Probability:** In this chapter we discuss the basic probability and axioms of probability, Basic concepts of statistics (mean, mode, variance and standard deviation), Discrete and continuous random variables and their distributions.
6. **Linear Algebra:** In this chapter we discuss the Special matrices, Algebra of matrices and their properties, inverse of a matrix, determinant of a matrix, solution of system of linear equations, LU decomposition method, Eigen values and Eigen vectors and finally we discuss the Cayley Hamilton theorem.
7. **Calculus:** In this chapter we discuss about Limits, continuity and differentiability, differentiation, partial derivatives, applications of differentiation (Mean value theorems, increasing and decreasing functions and maxima and minima of functions), methods of integration, and finally definite and indefinite integrals and their properties.




# Propositional Logic

## 1.1 PROPOSITIONAL LOGIC; FIRST ORDER LOGIC

**Logic:** In general logic is about reasoning. It is about the validity of arguments. Consistency among statements and matters of truth and falsehood. In a formal sense logic is concerned only with the form of arguments and the principle of valid inferencing. It deals with the notion of truth in an abstract sense.

**Truth Tables:** Logic is mainly concerned with valid deductions. The basic ingredients of logic are logical connectives, and, or, not, if.... then ....., if and only if etc. We are concerned with expressions involving these connectives. We want to know how the truth of a compound sentence like, " $x = 1$  and  $y = 2$ " is affected by, or determined by, the truth of the separate simple sentences " $x = 1$ ", " $y = 2$ ".

**Truth tables** present an exhaustive enumeration of the truth values of the component propositions of a logical expression, as a function of the truth values of the simple propositions contained in them. An example of a truth table is shown in table 1 below. The information embodied in them can also be usefully presented in tree form.



The branches descending from the node A are labelled with the two possible truth values for A. The branches emerging from the nodes marked B give the two possible values for B for each value of A. The leaf nodes at the bottom of the tree are marked with the values of  $A \wedge B$  for each truth combination of A and B.

## 1.2 LOGICAL CONNECTIVES OR OPERATORS

The following symbols are used to represent the logical connectives or operators.

And	$\wedge$ (Conjunction)
or	$\vee$ (Disjunction)
not	$\neg$ (Not)
Ex - or	$\oplus$
Nand	$\uparrow$
Nor	$\downarrow$
if....then	$\rightarrow$ (Implication)
if and only if	$\leftrightarrow$ (Biconditional)

1.  $\wedge$  (And / Conjunction): We use the letters F and T to stand for false and true respectively.

Table-1

A	B	$A \wedge B$
F	F	F
F	T	F
T	F	F
T	T	T

It tells us that the conjunctive operation  $\wedge$  is being treated as a **binary** logical connective—it operates on two logical statements. The letters A and B are “**Propositional Variables**”.

The table tells us that the compound proposition  $A \wedge B$  is true only when both A and B are true separately. The truth table tells us how to do this for the operator.  $A \wedge B$  is called a truth function of A and B as its value is dependent on and determined by the truth values of A and B.

A and B can be made to stand for the truth values of propositions as follows:

**A** : The cat sat on the mat

**B** : The dog barked

Each of which may be true or false. Then  $A \wedge B$  would represent the compound proposition “The cat sat on the mat and the dog barked”

$A \wedge B$  is written as A.B in Boolean Algebra.

2.  $\vee$  (Disjunction): The truth table for the disjunctive binary operation  $\vee$  tells us that the compound proposition  $A \vee B$  is false only if A and B are both false, otherwise it is true.

A	B	$A \vee B$
F	F	F
F	T	T
T	F	T
T	T	T

This is inclusive use of the operator ‘or’.

In Boolean Algebra  $A \vee B$  is written as  $A + B$ .

3.  $\neg$  (Not):

The negation operator is a “**unary operator**” rather than a binary operator like  $\wedge$  and its truth table is

A	$\neg A$
F	T
T	F

The table presents  $\neg$  in its role i.e., the negation of true is false, and the negation of false is true. Notice that  $\neg A$  is sometimes written as  $\sim A$  or  $A'$ .

**4.  $\oplus$  (Exclusive OR or Ex - OR):**

$A \oplus B$  is true only when either A or B is true but not when both are true or when both are false.

$A \oplus B$  is also denoted by  $A \vee - B$ .

A	B	$A \oplus B$
F	F	F
F	T	T
T	F	T
T	T	F

**5.  $\uparrow$  (NAND):**

$$P \uparrow Q \equiv \neg(P \wedge Q)$$

**6.  $\downarrow$  (NOR):**

$$P \downarrow Q \equiv \neg(P \vee Q)$$

**Note:**

$$P \uparrow P \equiv \neg P$$

$$P \downarrow P \equiv \neg P$$

$$(P \downarrow Q) \downarrow (P \downarrow Q) \equiv P \vee Q$$

$$(P \uparrow Q) \uparrow (P \uparrow Q) \equiv P \wedge Q$$

$$(P \uparrow P) \uparrow (Q \uparrow Q) \equiv P \vee Q$$

**7.  $\rightarrow$  (Implication):**

A	B	$A \rightarrow B$
F	F	T
F	T	T
T	F	F
T	T	T

Note that  $A \rightarrow B$  is false only when A is true and B is false. Also, note that  $A \rightarrow B$  is true, whenever A is false, irrespective of the truth value of B.

**8.  $\leftrightarrow$  (if and only if):** The truth table is

A	B	$A \leftrightarrow B$
F	F	T
F	T	F
T	F	F
T	T	T

Note that Bi-conditional (if and only if) is true only when both A & B have the same truth values.

( $A \leftrightarrow B$  may be written as  $A \iff B$ )

**Equivalences:**  $B \wedge A$  always takes on the same truth value as  $A \wedge B$ .

We say that  $B \wedge A$  is logically equivalent to  $A \wedge B$  and we can write this as follows  $B \wedge A \equiv A \wedge B$

**Definition:** Two expression are logically equivalent if each one always has the same truth value as the other.

Also,

$$B \wedge A \equiv A \wedge B$$

$$B \vee A \equiv A \vee B$$

$$A \wedge (B \wedge C) \equiv (A \wedge B) \wedge C$$

$$A \vee (B \vee C) \equiv (A \vee B) \vee C$$

These equivalence reveal  $\wedge$  and  $\vee$  to be commutative and associative operations. But these are not the only important equivalences that hold between logical forms.

A	B	$A \rightarrow B$	A	B	$\neg A$	$\neg A \vee B$
F	F	(T)	F	F	T	(T)
F	T	(T)	F	T	T	(T)
T	F	(F)	T	F	F	(F)
T	T	(T)	T	T	F	(T)

In the last columns in tables (Shown Bracketed) we have exactly same sequences of truth values. So,  $A \rightarrow B \equiv \neg A \vee B$ . Thus, we could do without the operation  $\rightarrow$ .

Now, consider the following two truth tables.

A	B	$A \wedge B$	A	B	$\neg A$	$\neg B$	$\neg A \vee \neg B$	$\neg(\neg A \vee \neg B)$
F	F	(F)	F	F	T	T	T	(F)
F	T	(F)	F	T	T	F	T	(F)
T	F	(F)	T	F	F	T	T	(F)
T	T	(T)	T	T	F	F	F	(T)

We see from the bracketed truth values that  $A \wedge B$  is logically equivalent to  $\neg(\neg A \vee \neg B)$ . Thus  $\wedge$  could be replaced by a combination of  $\neg$  and  $\vee$ .

Similarly we could show that  $\leftrightarrow$  can be replaced by a combination of  $\neg$  and  $\vee$ .

We say therefore that  $(\neg, \vee)$  forms a functionally complete set of connectives.

We can also show that  $(\neg, \wedge)$  also form a functionally complete set of connectives.

The NAND operator ( $\uparrow$ ) by itself is also a functionally complete set. So is the Nor operator ( $\downarrow$ ). These both are minimal functionally complete set.

Notice that  $(\vee, \wedge)$  is not a functionally complete set. Neither is  $(\neg)$ ,  $(\vee)$  or  $(\wedge)$  by themselves functionally complete.

### Example 1.1

Obtain the truth table for  $\alpha = (P \vee Q) \wedge (P \rightarrow Q) \wedge (Q \rightarrow P)$

**Solution:**

P	Q	$P \vee Q$	$P \rightarrow Q$	$(P \vee Q) \wedge (P \rightarrow Q)$	$Q \rightarrow P$	$\alpha$
T	T	T	T	T	T	T
T	F	T	F	F	T	F
F	T	T	T	T	F	F
F	F	F	T	F	T	F

**1.2.1 List of Important Equivalences**

$A \wedge 0 \equiv 0$	Domination law	$A \cdot 0 \equiv 0$
$A \vee 1 \equiv 1$	Domination law	$A + 1 \equiv 1$
$A \wedge 1 \equiv A$	Identity of $\vee$	$A \cdot 1 \equiv A$
$A \vee 0 \equiv A$	Identity of $\wedge$	$A + 0 \equiv A$
$A \wedge A \equiv A$	Idempotence	$A \cdot A = A$
$A \vee A \equiv A$	Idempotence	$A + A = A$
$A \wedge \neg A \equiv 0$	Complement law	$A \cdot A' = 0$
$A \wedge \neg A \equiv 1$	Complement law	$A + A' = 1$
$\neg\neg A \equiv A$	Law of double negation	$(A')' = A$
$A \wedge B \equiv B \wedge A$	Commutativity	$A \cdot B = B \cdot A$
$A \vee B \equiv B \vee A$	Commutativity	$A + B = B + A$
$A \vee (B \vee C) \equiv (A \vee B) \vee C$	Associativity	$A + (B + C) = (A + B) + C$
$A \wedge (B \wedge C) \equiv (A \wedge B) \wedge C$	Associativity	$A \cdot (B \cdot C) = (A \cdot B) \cdot C$
$A \wedge (B \vee C) \equiv (A \wedge B) \vee (A \wedge C)$	Distributivity	$A \cdot (B + C) = A \cdot B + A \cdot C$
$A \vee (B \wedge C) \equiv (A \vee B) \wedge (A \vee C)$	Distributivity	$A + (B \cdot C) \equiv (A + B) \cdot (A + C)$
$A \wedge (A \vee B) \equiv A$	Absorption law	$A \cdot (A + B) \equiv A$
$A \vee (A \wedge B) \equiv A$	Absorption law	$A + (A \cdot B) \equiv A$
$\neg(A \wedge B) \equiv \neg A \vee \neg B$	De Morgan's law	$(A \cdot B)' \equiv A' + B'$
$\neg(A \vee B) \equiv \neg A \wedge \neg B$	De Morgan's law	$(A + B)' \equiv A' \cdot B'$
$A \rightarrow B \equiv \neg A \vee B$		$A \rightarrow B \equiv A' + B$
$A \leftrightarrow B \equiv (A \rightarrow B) \wedge (B \rightarrow A)$		$A \leftrightarrow B \equiv (A' \rightarrow B) \cdot (B' \rightarrow A)$

**NOTE:**  $\oplus$  (EX – OR) is commutative and associative, (NAND) and (NOR) are both commutative but not associative.  $P \wedge (Q \oplus R) \equiv (P \wedge Q) \oplus (P \wedge R)$

**Simplification**

The various equivalence between logical forms provide us with a means of simplifying logical expressions. For example, we can simply the logical forms.

$(A \vee 0) \wedge (A \vee \neg A)$  as follows:

$$\begin{aligned} (A \vee 0) \wedge (A \vee \neg A) &= A \wedge (A \vee \neg A) \\ &= A \wedge 1 \text{ (since } A \vee \neg A \equiv 1) = A \end{aligned}$$

Similarly,  $(A \wedge \neg B) \wedge (A \wedge B \wedge C) \equiv A \wedge (\neg B \vee (B \wedge C))$

$$\begin{aligned} &\equiv A \wedge ((\neg B \vee B) \wedge (\neg B \vee C)) \\ &\equiv A \wedge (1 \wedge (\neg B \vee C)) \\ &\equiv A \wedge (\neg B \vee C) \end{aligned}$$

Since logic is a boolean algebra, it is always much easier to do simplification of logical expressions by converting them first into its boolean algebra equivalents.

**Example:**  $(A \vee 0) \wedge (A \vee \neg A) \equiv (A + 0) \cdot (A + A') = (A) \cdot (1) = A$

**Application to Circuit Design**

One of most important application of Boolean algebra is to the design of electronic circuits and especially to the design of computer logic. The basic logic functions ‘and’, ‘or’ and ‘not’ can be realised by electronic devices called gates and these can be combined together to form complicated circuits. The ‘and’ connective is realised by an ‘and-gate’ which is symbolised as follows:




The idea is that if the AND-gate receives input signals on both the A and B input lines, there will be an output signal on the line marked  $A \cdot B$ . If there is no input on either A or B or both there will be no output signal. Similarly, an 'OR-gate' is symbolised as follows:



If there is an input signal on either A or B or both, there will be an output signal on  $A + B$ .

Finally a NOT gate looks alike



In this case, if there is an input A, there will be no output and If there is no input A, there will be an output. The input is said to be inverted or negated.

Similarly we have the NAND gate and NOR gate represented y represented by.



### 1.3 WELL-FORMED FORMULAS (WFFS)

Consider  $P \wedge Q$  and  $Q \wedge P$ , where P and Q are any two propositions (logical statements). The truth table of these two propositions are identical. This happens when we have any proposition in place of P and any propositions in place of Q.

So we can develop the concept of propositional variable (corresponding to propositions) and well formed formulas (corresponding to propositions involving connectives).

**Definition:** A propositional variable is a symbol representing any proposition. We note that in algebra, a real variable is represented by the symbol  $x$ . This means that  $x$  is not a real number but can take a real value.

Similarly, a propositional variable is not a proposition but can be replaced by a proposition.

**Definition:** A well formed formula is defined as follows:

- (i) If P is a propositional variable then it is wff.
- (ii) If a is a wff, then  $\neg a$  is a wff.
- (iii) If  $\alpha$  and  $\beta$  are well formed formula, then  $(\alpha \vee \beta)$ ,  $(\alpha \wedge \beta)$ ,  $(\alpha \rightarrow \beta)$ ,  $(\alpha \leftrightarrow \beta)$  are well formed formula.

**NOTE:** A wff is not a proposition, but if we substitute the proposition in place of propositional variable, we get a proposition e.g.,  $(\neg P \wedge Q) \leftrightarrow Q$  is a wff.

Also note that " $P \neg \wedge Q \leftrightarrow Q$ " is not a wff. Similarly " $P \wedge Q \vee$ " is not a wff. This is because the above two cannot be derived using rules *i*, *ii* and *iii* given above for wffs.

#### Duality Law

Two formulas A and  $A'$  are said to be duals of each other, if either can be obtained from the other by replacing  $\wedge$  by  $\vee$ ,  $\vee$  by  $\wedge$ , 0 by 1 (F by T) and 1 by 0 (T by F). e.g., Dual of  $(P \wedge Q) \vee T$  is  $(P \vee Q) \wedge F$ , Dual of  $A + 1 = 1$  is  $A \cdot 0 = 0$

Let A and  $A'$  be duals consisting of  $P_1, P_2, \dots, P_n$  Propositional variables. By repeated application of De Morgan's Law, it can be shown that  $\neg A (P_1, P_2, \dots, P_n) = A' (\neg P_1, \neg P_2, \dots, \neg P_n)$ .

**Summary**



- Two expressions are logically equivalent if each one always has the same truth value as the other.
- $\oplus$  (EX – OR) is commutative and associative, (NAND) and (NOR) are both commutative but not associative.  $P \wedge (Q \oplus R) \equiv (P \wedge Q) \oplus (P \wedge R)$
- A wff is not a proposition, but if we substitute the proposition in place of propositional variable, we get a proposition e.g.,  $(\neg P \wedge Q) \leftrightarrow Q$  is a wff.
- When it is not clear whether a given formula is tautology, we can construct a truth table and verify that the truth value is T for all possible combinations of truth value of the propositional variables appearing in given formula.
- A **contradiction** (or absurdity) is a wff whose truth value is F for all possible assignments of truth values to the propositional variables.
- A **contingency** is a wff which is neither a tautology nor a contradiction. In other words, a contingency is a wff which is sometimes true or sometimes false.
- Two wff  $a$  and  $b$  in propositional variables  $P_1, P_2, \dots, P_n$  are **equivalent** if the formula  $a \leftrightarrow b$  is a tautology.
- For a given wff the PDNF form is unique the PCNF form is unique, if PDNF form or PCNF of 2 wffs are same, they are equivalent.
- Quantified parts of predicate formula such as  $\forall x P(x)$  or  $\exists x P(x)$  are propositions. We can assign values from the universe of discourse only to free variables in a predicate formula  $\alpha$ .



**Student's  
Assignments**

- Q.1** The logical expression  $((P \wedge Q) \Rightarrow (R' \wedge P)) \Rightarrow P$
- a tautology
  - a contradiction
  - a contingency
  - All the above

- Q.2** The principal conjunctive normal form is
- sum of products
  - product of sums
  - sum of max-terms
  - product of max-terms

- Q.3** Match **List-I** with **List-II** and select the correct answer using the codes given below the lists:

**List-I**

- Associative law
- Absorption law
- Demorgans law
- Commutative

**List-II**

- $P \vee (Q \vee R) \equiv (P \vee Q) \vee R$
- $P \vee Q \equiv Q \vee P$
- $\neg(P \vee Q) \equiv \neg P \wedge \neg Q$
- $P \vee (P \wedge Q) \equiv P$

**Codes:**

- |     | A | B | C | D |
|-----|---|---|---|---|
| (a) | 1 | 2 | 3 | 4 |
| (b) | 4 | 3 | 1 | 2 |
| (c) | 1 | 4 | 3 | 2 |
| (d) | 2 | 1 | 4 | 2 |

- Q.4** Consider the following statements:

$S_1: R \vee (P \vee Q)$

is a valid conclusion from the premises

$P \vee Q, R \rightarrow Q, M \rightarrow P$  and  $\neg M$

$S_2: a \rightarrow b, \neg(f \vee c) \Rightarrow \neg b$

then

- $S_1$  is true and  $S_2$  is invalid
- $S_1$  is false and  $S_2$  is invalid
- Both are true
- Both are false

- Q.5** The following propositional statement is  
 $[(p \rightarrow r) \wedge (q \rightarrow r)] \rightarrow [(p \vee q) \rightarrow r]$   
 (a) tautology  
 (b) contradiction  
 (c) neither tautology nor contradiction  
 (d) not decidable
- Q.6** Identify the correct translation into logical notation of the following assertion  
 "All connected bipartite graphs are nonplanar"  
 (a)  $\forall x \left[ \begin{array}{l} \sim \text{connected}(x) \vee \sim \text{bipartite} \\ (x) \wedge \sim \text{planar}(x) \end{array} \right]$   
 (b)  $\forall x \left[ \begin{array}{l} \sim \text{connected}(x) \vee \sim \text{bipartite} \\ (x) \vee \sim \text{planar}(x) \end{array} \right]$   
 (c)  $\forall x \left[ \begin{array}{l} \sim \text{connected}(x) \wedge \sim \text{bipartite} \\ (x) \wedge \sim \text{planar}(x) \end{array} \right]$   
 (d)  $\forall x \left[ \begin{array}{l} \sim \text{connected}(x) \wedge \sim \text{bipartite} \\ (x) \vee \sim \text{planar}(x) \end{array} \right]$
- Q.7** Which of the following statements are true?  
 (i) It is not possible for the propositions  $P \vee Q$  and  $\neg P \vee \neg Q$  to be both false. To be both false.  
 (ii) It is possible for the proposition  $P \rightarrow (\neg P \rightarrow Q)$  to be false.  
 (a) Only (i) is true  
 (b) Only (ii) is true  
 (c) Both (i) and (ii) are true  
 (d) Both (i) and (ii) are false
- Q.8** Which of the following statements are true?  
 (i)  $((P \rightarrow Q) \rightarrow R) \rightarrow ((R \rightarrow Q) \rightarrow P)$  is a tautology  
 (ii) Let A, B be finite sets, with  $|A| = m$  and  $|B| = n$ . The number of distinct functions  $f : A \rightarrow B$  is there from A to B is  $m^n$ .  
 (a) Only (i) is true  
 (b) Only (ii) is true  
 (c) Both (i) and (ii) are true  
 (d) Both (i) and (ii) are false
- Q.9** State whether the following statements are true or false?  
 (i)  $(P \Rightarrow Q) \Rightarrow (Q \Rightarrow P)$  always holds, for all proposition P, Q.  
 (ii)  $((P \vee Q) \Rightarrow Q) \Rightarrow (Q \Rightarrow (P \vee Q))$  always holds, for all propositions P.  
 (a) (i) is true, (ii) is false  
 (b) Both (i) and (ii) are true  
 (c) (i) is false, (ii) is true  
 (d) Both (i) and (ii) are false
- Q.10** Which of the following is tautology?  
 (a)  $x \vee y \rightarrow y \wedge z$   
 (b)  $x \wedge y \rightarrow y \vee z$   
 (c)  $x \vee y \rightarrow y \rightarrow z$   
 (d)  $x \rightarrow y \rightarrow (y \rightarrow z)$
- Q.11** Suppose  
 $P(x)$  : x is a person.  
 $F(x, y)$  : x is the father of y.  
 $M(x, y)$  : x is mother of y.  
 What does the following indicates  
 $(\exists z) (P(z) \wedge F(x, z) \wedge M(z, y))$   
 (a) x is father of mother of y  
 (b) y is father of mother of x  
 (c) x is father of y  
 (d) None of the above
- Q.12** Give the converse of "If it is raining then I get wet".  
 (a) If it is not raining then I get wet  
 (b) If it is not raining then I do not get wet  
 (c) If it get wet then it is raining  
 (d) If I do not get wet then it is not raining
- Q.13** Which of the following is true?  
 (a)  $\neg(p \Rightarrow q) \equiv p \wedge \neg q$   
 (b)  $\neg(p \leftrightarrow q) \equiv ((p \vee \neg q) \vee (q \wedge \neg p))$   
 (c)  $\neg(\exists x (p(x) \Rightarrow q(x))) \equiv \forall x (p(x) \Rightarrow q(x))$   
 (d)  $\exists x p(x) \equiv \forall x p(x)$

**Answer Key:**

1. (c)    2. (d)    3. (c)    4. (a)    5. (a)  
 6. (b)    7. (a)    8. (d)    9. (c)    10. (b)  
 11. (a)    12. (c)    13. (a)



**Student's Assignments** | Explanations

**1. (c)**

The logical expression  $((P \wedge Q) \Rightarrow (R' \wedge P)) \Rightarrow P$  can be converted in Boolean Algebra notation as,

$$\begin{aligned} (pq \Rightarrow r' p) \Rightarrow p & \\ \equiv ((pq)' + r' p) \Rightarrow p & \\ \equiv (p' + q' + r' p) \Rightarrow p & \\ \equiv ((p' + r' p) + q') \Rightarrow p & \\ \equiv ((p' + p) \cdot (p' + r') + q') \Rightarrow p & \\ \equiv (p' + r' + q') \Rightarrow p & \\ \equiv (p' + r' + q')' + p \equiv prq + p & \\ \equiv p & \end{aligned}$$

$\therefore$  The given expression is a contingency.

**4. (a)**

$S_1 : P \vee Q, R \rightarrow Q, M \rightarrow P, \sim M \Rightarrow R \vee (P \vee Q)$   
In boolean algebra notation the above expression is written as

$$\begin{aligned} (p + q) \cdot (q + r') \cdot (p + m') \cdot m' \Rightarrow r + p + q & \\ \equiv (q + pr') (m') \Rightarrow r + p + q & \\ \equiv qm' + pr'm' \Rightarrow r + p + q & \\ \equiv (qm' + pr'm') + r + p + q & \\ \equiv (q' + m) (p' + r + m) r + p + q & \\ \equiv q'p' + q'r + q'm + mp' + mr + m + r + p + q & \\ \text{(by absorption law)} \equiv q'p' + r + m + p + q & \\ \equiv (p + p') \cdot (p + q') + r + m + q & \\ \equiv p + q' + r + m + q & \\ \equiv p + r + m + 1 \equiv 1 & \end{aligned}$$

$\therefore S_1$  is true

$S_2 : a \rightarrow b, \neg (f \vee c) \Rightarrow \neg b$

In boolean Algebra notation

$$\begin{aligned} S_2 \equiv (a \rightarrow b) \cdot (f \vee c)' \Rightarrow b' & \\ \equiv (a' + b) \cdot (f'c') \Rightarrow b' & \\ \equiv [(a' + b) \cdot (f'c')] + b' & \\ \equiv (a' + b)' + (f'c')^1 + b' & \\ \equiv ab' + f + c + b' & \\ \equiv f + c + b' & \end{aligned}$$

which is a contingency

$\therefore S_2$  is invalid.

**5. (a)**

$$\begin{aligned} [(p \rightarrow r) \wedge (q \rightarrow r)] \rightarrow [(p \vee q) \rightarrow r] & \\ \equiv (p' + r) (q' + r) \rightarrow (p + q)' + r & \\ \equiv (r + p'q')' \rightarrow (p + q)' + r & \\ \equiv (r + p'q')' + (p + q)' + r & \\ \equiv r'(p'q')' + p'q' + r & \\ \equiv r'(p + q)' + p'q' + r & \\ \equiv r'p + r'q + p'q' + r & \\ \equiv (r + r') \cdot (r + p) + r'q + p'q' & \\ \equiv r + p + r'q + p'q' & \\ \equiv (r + r') (r + q) + (p + p') (p + q') & \\ \equiv r + q + p + q' & \\ \equiv r + p + 1 \equiv 1 & \\ \therefore \text{tautology} & \end{aligned}$$

**6. (b)**

The correct translation is

$$\forall x[(\text{connected}(x) \wedge \text{bipartite}(x)) \rightarrow \sim \text{planar}(x)]$$

however, since  $p \rightarrow q \equiv \sim p \vee q$ , we can write the above expression also as,

$$\forall x[\sim \text{connected}(x) \vee \sim \text{bipartite}(x) \vee \sim \text{planar}(x)]$$

**7. (a)**

If  $P \vee Q$  is false, then both P and Q are false.

$$\text{So, } \neg P \vee \neg Q \equiv \neg F \vee \neg F \equiv T \vee T \equiv T$$

$\therefore (i)$  is true

Consider  $(ii)$

$$\begin{aligned} P \rightarrow (\neg P \rightarrow Q) & \equiv P \rightarrow (P^1 \rightarrow Q) \\ & \equiv P \rightarrow P + Q \\ & \equiv P^1 + P + Q \equiv 1 + Q \equiv 1 \end{aligned}$$

It is a tautology, So  $(ii)$  is false.

**8. (d)**

$(i)$  Using boolean algebra, we can shown that the given expression reduces to  $P + R' + Q'$  which is not a tautology.

$(ii)$  For each element  $a \in A$ , we have  $n$  possible choices for value of  $f(a)$ . Thus there are  $n^m$  possible functions.

**9. (c)**

$$\begin{aligned} (i) (P \Rightarrow Q) \Rightarrow (Q \Rightarrow P) & \\ \equiv (P' + Q) \rightarrow (Q' + P) & \\ \equiv (P' + Q)' + Q' + P & \\ \equiv PQ' + Q' + P \equiv P + Q' & \end{aligned}$$